

## DRYWALL TRIMLESS - INSTALLATION INSTRUCTIONS




## NOTE: Wire dimming conductors as Class 1




Prepare the area where the fixture is going to be installed. Cut hole in the drywall according to the dimensions [\*] in the client drawings.




Remove reflector [A] from the extrusion. Disconnect quick connectors [B] and remove security cables [C] in order to remove the reflector [A]. Place it in a safe place.




Install power cable [D] (by other) through the BX connector [E] (by other) and install onto the power plate [F] provided. Make electrical connections between power cable [D] and fixture cables using electrical marettes [G]. Reinstall the power plate [F] to the fixture [H]. Insert fixture into pre-cut hole in drywall.



Insert fixture [H] into pre-cut hole in drywall, aligning threaded rods [I] with holes in top of fixture [H].Put washers [J] and tighten nuts [K] to secure the fixture [H].



Reinstall security cables [C] and reconnect quick connectors [B]. Reinstall reflector [A] inside the fixture.




Prepare the area where all the fixtures are going to be installed. Cut hole in the drywall according to the dimensions [\*] in the client drawings.




## **CAVA**

## DRYWALL TRIMLESS - INSTALLATION INSTRUCTIONS







Remove reflectors [A] from the extrusion. Disconnect quick connectors [B] and remove security cables [C] in order to remove the reflectors [A]. Place them in a safe place. Repeat for all fixtures in the run.




Apply steps 3 and 4 to the first fixture [H] in the run. Make wires connection between fixtures [H] and [L] using quick connectors [B].



Align threaded rods [I] with holes in top of the fixtures. Put washers [J] and tighten nuts [K] to secure the fixtures.



Tighten the set screws [M] on both joining brackets [N] using Allen Key to secure the fixtures together.



Reinstall security cables [C] and reconnect quick connectors [B]. Reinstall reflectors [A] inside the fixtures.

