

NOTE: Wire dimming conductors as Class 1

1

SIDE VIEW

Locate wall bracket position using provided client drawing. Install mounting brackets (A) to wall. Align with structural stud (need double studs – distance between studs is 1.250”) or use metal anchors with min. length 1.250”. Flat head Philips drive screw, nominal size #10, min. length 1.250”.

2

Make electrical connection between fixture (B) and wall power cable (C).

3

Insert fixture bracket (D) into wall bracket (A), and secure it in place with supplied screw (E).

4 CONTINUOUS SYSTEM

Unscrew and lift up the top plates (F).

5

Remove the screws (G) on the joiner and put them in a safe place.

6

SIDE VIEW

Locate wall bracket position using provided client drawing. Install mounting brackets (A) to wall. Align with structural stud (need double studs – distance between studs is 1.250”) or use metal anchors with min. length 1.250”. Flat head Philips drive screw, nominal size #10, min. length 1.250”.

